
Operating Instructions





1. When the product is unpowered, both the light icon and radar icon appear gray (no backlight).

2. After powering on:

- · The light icon turns white, and the radar icon displays a light ice blue.
- · After 5 seconds, the radar activates and begins scanning.
- · When human motion is detected, the light turns on, and both icons glow ice blue.
- · Single-tap the touch key:

The light turns off (light icon returns to *white*).

The radar enters 30-second standby mode (radar icon reverts to light ice blue).

When the 30-second standby period ends, the radar automatically resumes sensing (standby mode):

- · Light icon: White (indicates manual mode)
- · Radar icon: Ice blue (indicates active sensing readiness)

3. Motion-Activated Lightingd

- · When human motion is detected, the light turns on for 10 minutes.
- The timer resets and extends by 10 minutes with each subsequent detection within the active period.
- Soft transitions:
- *Light fades on when activated.
- *Light fades off when turned off.

4. Anti-Fog Film Synchronization

The anti-fog film activates automatically when the light is on and deactivates when the light turns off.

5. Manual Light Control & Color Temperature Adjustment

While the light is on:

Single-tap the touch key to cycle through color temperatures: Warm White (3000K) \rightarrow Cool White (6000K) \rightarrow Neutral (4000K) \rightarrow OFF. (5-second selection window).

If no touch input is detected for 8 seconds, the next touch will turn off the light (Light icon: White | Radar icon: Light Ice Blue).

After light turns off:

If no interaction occurs within 30 seconds, the radar resumes standby mode (Light icon: White | Radar icon: Ice Blue).

Memory Function: The last selected color temperature is saved and reapplied upon reactivation.

6. Disabling Radar Function (Manual Mode)

Long-press (2 sec) the light key to disable radar sensing:

Light icon: White | Radar icon: No backlight (Gray).

Only manual touch control remains (no timer/motion sensing).

7. Re-Enabling Radar Function

Long-press (2 sec) the light key again to restore radar function:

Light icon: White | Radar icon: Ice Blue.

Motion detection, timer, and auto-lighting resume normal operation.

8. Radar Detection Range & Angle

Range: Up to 1.5 meters in front of the mirror.

Detection angle: 60°-80° (forward-facing cone).